

Net2 - Hands free interface

System specifications

| | |
|---|----------------|
| Readers per interface | 1 |
| Entry confirmation input | Yes |
| Maximum cable extension length between ACU and interface | 100m/328ft |
| Maximum cable extension length between interface and reader | 15m/49ft |
| Cable type for extensions | Belden 9540 |
| Additional power supply required | No |
| Read range: P38 | Up to 850 mm* |
| Read range: P50 | Up to 1100 mm* |
| Read range: P75 | Up to 1500 mm* |
| Read range: P200 | Up to 2500 mm* |
| Read range: P200 metal mount | Up to 2000 mm* |
| Clock and data bit period | 600µs |


* All read ranges are maximum distances. Radio products can be affected by site conditions, this means that these distances are not achieved in all cases.

Electrical

| | |
|---------------------|-----------------|
| Operating voltage | 11V DC - 14V DC |
| Current consumption | 80 mA |
| Carrier frequency | 2.4GHz |

Environment

| | |
|-----------------------|---|
| Operating temperature | -20°C - +55°C |
| Waterproof | No - If used externally, it must be protected in a weatherproof housing |



When you fit an access control system in a building, doors are controlled with proximity readers. When you reach a door an authorised token is presented directly to the reader. In most situations this is efficient and convenient. Sometimes, however, it is useful to go through doorways without stopping to present a token. Especially if your hands are full. Fitting our Hands free interface means that the door unlocks as the user approaches.


Hands free access opens up a number of possibilities for any site. It helps companies to easily conform to the Disability Discrimination Act (DDA), ensuring a building provides adequate disabled access. Companies have a legal responsibility to take 'reasonable' steps to provide disabled access. Hands free entry is also extremely useful to provide ease of access through doors in warehouses or to provide contactless hygienic access in hospitals and 'clean room' environments.

Unlike most hands free solutions available for access control systems, there is a choice from a range of stylish and discreet readers. A building is not compromised by large unsightly readers. The read range remains excellent; you get the best of both worlds.

Installing hands free access usually requires a huge investment in time and money. With Paxton Access hands free, the installation costs are low and it is not time consuming to fit it.

The great thing about Paxton Access hands free access is that you don't have to make your decision straight away; if you think this is a feature that might be needed in the future, fitting it to an existing system couldn't be easier. It also means that hands free tokens are only given to the people that need them. The hands free enabled reader will still work as a proximity reader for those using standard tokens.

Hands free access from Paxton Access is simple, economic and flexible.



Sales codes and accessories

| | |
|--|----------|
| Proximity handsfree interface - with plastic housing | 477-222 |
| Net2 - Hands free keyfob | 690-222 |
| Switch2 - Handsfree keyfob, Green, pack of 10 | 860-010G |